

Argus Series B310

Wireless Battery Security Camera with 3MP Super HD, Smart Detection, Two-Way Audio & Solar Power Option

- 3MP Super HD
- People/Vehicle/Animal Detection
- Color Night Vision
- No Monthly Fee



Specifications

Video & Audio	
Image Sensor	1/2.7" CMOS sensor
Resolution	2304x1296 (3 megapixels) @15fps
Lens	f=4mm , F=2.0
Video Compression	H.264/H.265
Field of View	Diagonal: 115° Horizontal: 88° Vertical: 50°
Infrared Night Vision	Up to 10 meters (33ft); LED: 6pcs/0.8W/850nm (Auto-switching with IR-cut filter)
Color Night Vision	With spotlights: 2pcs/2W/6500K
Frame Rate	Main stream: 10fps - 15fps (default: 15fps) Sub stream: 10fps - 15fps (default: 15fps)

Code Rate	Main stream: 1024Kbps - 2048Kbps (default: 2048Kbps) Sub stream: 64Kbps - 256Kbps (default: 192Kbps)
Audio	Two-way audio
Power	
Battery	6000mAh rechargeable battery (Battery life varies based on settings, usage & temperature.)
Solar	Reolink Solar Panel (3W)
Interface	
Power Port	USB Type-C port
SD Card Slot	Supports Max. 128GB microSD card
Reset Button	YES
Audio In/Out	Built-in microphone and speaker
Wi-Fi	
Wireless Standard	IEEE 802.11 b/g/n
Operating Frequency	2.4GHz
Wireless Security	WPA-PSK/WPA2-PSK
Software	
OS Supported	PC: Windows, Mac OS; Smartphone: iOS, Android
Protocols & Standards	SSL, TCP/IP, UDP, UPNP, SMTP, NTP, P2P
User Access	Max. 12 simultaneous streams (2 main & 10 sub streams)
Other Feature(s)	
Smart Alarm	PIR detection; motion detection; person detection; vehicle detection; animal detection
PIR Detecting Distance	Adjustable, up to 10m (33ft)
PIR Detecting Angle	100° horizontal

Recording Modes	Triggered recording
Time Lapse	YES
Smart Home Compatibility	Google Assistant
Home Hub Compatibility	YES
Cloud Storage	Supports Reolink Cloud (available in selected countries)
Working Environment	
Operating Temperature	-10°C~55°C (14°F~131°F)
Operating Humidity	20% ~ 85%
Weatherproof	IP65
Mechanical	
Dimensions	127*90*56mm
Weight (Without Bracket)	239g
Warranty	
Limited Warranty	2-year limited warranty. For support, visit https://support.reolink.com/hc/en-us/ .